



Stage Lighting Equipment Supplier Expert

WELCOME TO JOIN US

USER'S MANUAL

LED Beam+Wash Double Sides 4 x10W + 1 x10W Lighting



Maintenance

1. Please keep the light in dryness and avoiding use in wet place.
2. Using intermittently can be extended the life.
3. Attention to clean the fan and lens usually in order to get the ventilating effects and lighting effects better.
4. Please do not wipe the crust using organic menstruum for avoid to damaged the product.

Statement

The product has well capability and intact packing when leave factory, All of the user should comply with above warning item and manual, any misuse cause of the damages are not included in our guarantee, and also can't be responsible for any malfunction & problem owing to ignore the manual. Please forgive that we will not be notice for technical change

Attention Item

1. For guarantee the life of product, please do not put it on the wet place and not use it the place over 40 degree.
2. Please don't lay the product on the un-fixable or shakable place.
3. Ask for the professional to maintain the product in order to avoid the danger of get an electric

shock.

4. Power supply should not be changed over $\pm 10\%$ while the light is using, it will be decreased the life of lamp if the power is too high, but it will be influenced the luminosity if the power is too low.

5. After power off, if it is need used again, please cool down over 20 minutes.

6. Please look round the manual for ensure the product can be used normally.

DMX Channel Summary-21 Channels Mode

Channel	Value	Features
CH1	0-255	X axis rotation
CH2	0-255	X-axis fine-tuning
CH3	0-255	Y axis rotation
CH4	0-255	Y axis fine-tuning
CH5		Y axis rotation Infinite
CH6		XY speed adjustment
CH7	0-255	Total light adjustment
CH8	0-250	Strobe focusing
CH9	0-255	Red Dimmer
CH10	0-255	Green Dimmer
CH11	0-255	Blue Dimmer
CH12	0-255	White Dimmer
CH13	0-255	Red2 Dimmer
CH14	0-255	Green2 Dimmer
CH15	0-255	Blue2 Dimmer
CH16	0-255	White2 Dimmer
CH17	16-255	Motor auto
CH18	0-255	Motor auto-Speed
CH19	0-255	Auto
CH20	0-255	Auto-Speed
CH21	250-255	Rest

DMX Channel Summary-15 Channels Mode

Channel	Value	Features
CH1	0-255	X axis rotation
CH2	0-255	Y axis rotation
CH3	0-255	Y axis rotation Infinite
CH4	0-255	XY speed adjustment
CH5	0-255	Total light adjustment
CH6	0-255	Strobe
CH7	0-255	Red Dimmer
CH8	0-255	Green Dimmer
CH9	0-255	Blue Dimmer
CH10	0-255	White Dimmer
CH11	0-255	XY axis Auto Run
CH12	0-255	Motor auto-Speed
CH13	0-255	000-175.....Preset color 176-200.....Program jump 201-224.....Program gradient 225-255.....Program pulse
CH14	0-255	Program speed adjustment
CH15	250-255	Rest

Display Control Instruction

Addr	A001-A512	512 DMX
CHnd	21CH	21CH
	15CH	15CH
SLnd	MAST	AUTO

	Soun	SOUND
	SL 1	DMX
	SL 2	
SHnd	SH 0	Effect 0
	SH 1	Effect 1
	SH 2	Effect 2
	SH 3	Effect 3
SEnS	0-99	sound -speed
bLAnd	bLAc	No DMX-0
	Auto	No DMX-Sound
	Soun	No DMX-Auto
	HoLd	No DMX-Auto1
LEd	OFF	Show-Off
	ON	Show-On
dISP	no	Show-P
	YES	Show-R
rPAN	no	X-motor-P
	YES	X-motor-R
rTiL	no	Y-motor-P
	YES	Y-motor-R
REST	YES	REST

Product Introduction

- * Power Supply:AC90--275V,50--60HZ
- * Power consumption:50W
- * Fixing lamp:LED 4 x10W + 1 x10W RGBW
- * DMX-Control-channels:15/21 DMX Channels
- * Shuttle:Flash rate:0--10HZ
- * Dimmer:0-100% mechanic dimmer
- * Long Lifespan LEDs(more than 60,000 hours)