



Stage Lighting Equipment Supplier Expert

WELCOME TO JOIN US

USER'S MANUAL

LED Beam+Wash Big Bees Eyes 7x15W RGBW Zoom Lighting



Maintenance

1. Please keep the light in dryness and avoiding use in wet place.
2. Using intermittently can be extended the life.
3. Attention to clean the fan and lens usually in order to get the ventilating effects and lighting effects better.
4. Please do not wipe the crust using organic menstruum for avoid to damaged the product.

SHEHDS

1. TECHNICAL PARAMETERS

Input power: AC100-240V 50/60Hz

LED: 7PCS 15W high power RGBW LED

DMX channel: 17/23/43 CH

Movement: Pan/Tilt: X axis 540°, Y axis 190°

Control mode: DMX512/Master-Slave /Auto run

Strobe macro control available, Focus: Electronic focus

Display: LCD display

Ip Rate: IP20

2. MENU FUNCTION

1.	DMX Settings	DMX512 Address	001-512
2.		Channel Settings	17/23/43.CH
3.	Run Mode		DMX/Slow/Fast/Sound/Manual
4.	Invert PAN/TILT		Yes/No
5.	Display Set	Invert Word	Yes/No
6.		English/Chinese	EN/CH
7.		LCD Backlight On	Yes/No
8.	Manual Set	PAN	000-255
		TILT	000-255
		XY-SPEED	000-255
		ROTATION	000-255
		ROTATION-SP	000-255
		ZOOM	000-255
		DIM	000-255
		STROBE	000-255
		DIM-R/G/B/W	000-255
		STA-CH	000-255
		MOV-SP	000-255
		MACRO-CH	000-255
9.	Sound sense		0%-100%
10.	System Set	System Information	
11.		Default Settings	Yes/No
12.		Code Settings	Setting your password
13.	Reset	Reset System	Yes/No

3.DMX Channel list

CH17	CH23	CH43	Channel	DMX date	Function
1	1	1	Pan	0-255	Pan rotation 540°
	2	2	Pan Fine	0-255	Pan Fine 5°
2	3	3	Tilt	0-255	Tilt rotation 270°
	4	4	Tilt Fine	0-255	Tilt Fine 3°
3	5	5	Pan/Tilt Speed	0-255	Pan/Tilt Speed From fast to slow
4	6	6	Zoom rotation	0-127	0-60°
				128-191	Clockwise
				192-255	Anticlockwise
5	7	7	Rotation Speed	0-255b	Rotation Slow to Fast
6	8	8	Zoom	0-255	Narrow Beam-Wide Beam
7	9	9	Main Dimming	0-255	Total Dimming
8	10	10	Strobe	0-255	Strobe Flash
9	11	11	LED1 Dimming	0-255	R1 Dimming 0-100%
10	12	12		0-255	G1 Dimming 0-100%
11	13	13		0-255	B1 Dimming 0-100%
12	14	14		0-255	W1 Dimming 0-100%
	15	15	LED2 Dimming	0-255	R2 Dimming 0-100%
	16	16		0-255	G2 Dimming 0-100%
	17	17		0-255	B2 Dimming 0-100%
	18	18		0-255	W2 Dimming 0-100%
		...	...	...	...
		35	LED7 Dimming	0-255	LED R7 Dimming 0-100%
		36		0-255	LED G7 Dimming 0-100%
		37		0-255	LED B7 Dimming 0-100%
		38		0-255	LED W7 Dimming 0-100%
13	19	39	Shape	0-255	Shape
14	20	40	Dynamic Shape	0-255	Shape Transition Effect
15	21	41	Shape Speed	0-255	Fast to Slow
16	22	42	Function Control	50-99	Shape (Built-in effect)Have Function on 9/39/41CH
				100-149	Dynamic Shape (Built-in effect)Have Function on 9/40/41

		42		150-199	Auto mode
				200-255	Sound Control
17	23	43	Reset	251-255	After 3S reset system

SHEHDS